

Power Distribution Unit

1U NEMA 20A Series - Power Distribution Unit

Ahoku PDU units are available in a variety of 15A and 20A / 120V NEMA configurations. Unit configurations include 19" horizontals. Heavy duty powder coated steel housings (1U) provide for a long lasting sturdy construction. Parallel circuitry enables these units to continue functioning as a power strip, even if surge suppression is disabled by surge or spike.



**1U NEMA 20A Series -
Power Distribution Unit**

Safety Approval



Feature

- ◆ Power Current/ Voltage/ Wattage meter.
- ◆ AC power line surge protector. Protect high-tech electronic devices from damage caused by dangerous spikes/surges that coming from AC power line.
- ◆ Equipped with circuit breaker for overload protection.

Specification

Model	5-20R Front	5-20R Rear	Switch	Surge Protection	Indicator (Power / Surge)	Power Cord 12AWG (01 / 02)	Amp Meter
PD-082001A0	0	8	C.B.	N/A	Pwr-red	5-20P / 6Ft / BLK	✗
PD-082001A1	0	8	C.B.	L-N	Pwr-red, Surge-green	5-20P / 6Ft / BLK	✗
PD-082001A2	0	8	C.B.	L-N-G	Pwr-red, Surge-green	5-20P / 6Ft / BLK	✗
PD-082001A3	0	8	C.B.	L-N-G + Noise Filter	Pwr-red, Surge-green	5-20P / 6Ft / BLK	✗
PD-082001A0MI	0	8	C.B.	N/A	Pwr-red	5-20P / 6Ft / BLK	Yes
PD-082002A0	0	8	C.B.	N/A	Pwr-red	L5-20P / 6Ft / BLK	✗
PD-082002A1	0	8	C.B.	L-N	Pwr-red, Surge-green	L5-20P / 6Ft / BLK	✗
PD-082002A2	0	8	C.B.	L-N-G	Pwr-red, Surge-green	L5-20P / 6Ft / BLK	✗
PD-082002A3	0	8	C.B.	L-N-G + Noise Filter	Pwr-red, Surge-green	L5-20P / 6Ft / BLK	✗
PD-082002A0MI	0	8	C.B.	N/A	Pwr-red	L5-20P / 6Ft / BLK	Yes
PD-102001A0	2	8	C.B.	N/A	Pwr-red	5-20P / 6Ft / BLK	✗
PD-102001A1	2	8	C.B.	L-N	Pwr-red, Surge-green	5-20P / 6Ft / BLK	✗
PD-102001A2	2	8	C.B.	L-N-G	Pwr-red, Surge-green	5-20P / 6Ft / BLK	✗
PD-102001A3	2	8	C.B.	L-N-G + Noise Filter	Pwr-red, Surge-green	5-20P / 6Ft / BLK	✗
PD-102001A0MI	2	8	C.B.	N/A	Pwr-red	5-20P / 6Ft / BLK	Yes
PD-102002A0	2	8	C.B.	N/A	Pwr-red	L5-20P / 6Ft / BLK	✗
PD-102002A1	2	8	C.B.	L-N	Pwr-red, Surge-green	L5-20P / 6Ft / BLK	✗
PD-102002A2	2	8	C.B.	L-N-G	Pwr-red, Surge-green	L5-20P / 6Ft / BLK	✗
PD-102002A3	2	8	C.B.	L-N-G + Noise Filter	Pwr-red, Surge-green	L5-20P / 6Ft / BLK	✗
PD-102002A0MI	2	8	C.B.	N/A	Pwr-red	L5-20P / 6Ft / BLK	Yes
PD-122001A0	4	8	C.B.	N/A	Pwr-red	5-20P / 6Ft / BLK	✗
PD-122001A1	4	8	C.B.	L-N	Pwr-red, Surge-green	5-20P / 6Ft / BLK	✗
PD-122001A2	4	8	C.B.	L-N-G	Pwr-red, Surge-green	5-20P / 6Ft / BLK	✗
PD-122001A3	4	8	C.B.	L-N-G + Noise Filter	Pwr-red, Surge-green	5-20P / 6Ft / BLK	✗
PD-122001A0MI	4	8	C.B.	N/A	Pwr-red	5-20P / 6Ft / BLK	Yes
PD-122002A0	4	8	C.B.	N/A	Pwr-red	L5-20P / 6Ft / BLK	✗
PD-122002A1	4	8	C.B.	L-N	Pwr-red, Surge-green	L5-20P / 6Ft / BLK	✗
PD-122002A2	4	8	C.B.	L-N-G	Pwr-red, Surge-green	L5-20P / 6Ft / BLK	✗
PD-122002A3	4	8	C.B.	L-N-G + Noise Filter	Pwr-red, Surge-green	L5-20P / 6Ft / BLK	✗
PD-122002A0MI	4	8	C.B.	N/A	Pwr-red	L5-20P / 6Ft / BLK	Yes
PD-142001A0	6	8	C.B.	N/A	Pwr-red	5-20P / 6Ft / BLK	✗
PD-142001A1	6	8	C.B.	L-N	Pwr-red, Surge-green	5-20P / 6Ft / BLK	✗
PD-142001A2	6	8	C.B.	L-N-G	Pwr-red, Surge-green	5-20P / 6Ft / BLK	✗
PD-142001A3	6	8	C.B.	L-N-G + Noise Filter	Pwr-red, Surge-green	5-20P / 6Ft / BLK	✗
PD-142001A0MI	6	8	C.B.	N/A	Pwr-red	5-20P / 6Ft / BLK	Yes
PD-142002A0	6	8	C.B.	N/A	Pwr-red	L5-20P / 6Ft / BLK	✗
PD-142002A1	6	8	C.B.	L-N	Pwr-red, Surge-green	L5-20P / 6Ft / BLK	✗
PD-142002A2	6	8	C.B.	L-N-G	Pwr-red, Surge-green	L5-20P / 6Ft / BLK	✗
PD-142002A3	6	8	C.B.	L-N-G + Noise Filter	Pwr-red, Surge-green	L5-20P / 6Ft / BLK	✗
PD-142002A0MI	6	8	C.B.	N/A	Pwr-red	L5-20P / 6Ft / BLK	Yes

AHOKU ELECTRONIC COMPANY

5F, NO.88, Sec.1, Nei-Hu Rd., Taipei, Taiwan

TEL:886-2-27991199 FAX:886-2-27999099

Copyright © AHOKU Electronic Company. All Rights Reserved